

ARCONIC

Innovation, engineered.

Frangible Collar Assembly Tools



April 27, 2018


Tool Selection

How to Specify Your Tool Selection:

1. Identify the fastener type and diameter by part number.
2. Identify the installed torque range of the fastener.
3. What is the hex size of the collar? Example: 1/4" = 250
4. Does a pistol grip tool or a straight motor fit the application best?
5. Most tools can be equipped with a 360° index unit that will help with application accessibility.
6. Would the tool fit best with an extended socket or a flush socket?
7. Are the threaded pins interference fit or loose? If they are loose a hex key would be required.
8. Don't see the tool you need? We have 100's of tool models not listed in this catalog.
9. Need Additional Help? Please call us for assistance, 714-278-8908

Example of Complete Tool Model Number:


CTL1429 C 343 D 078





Hex Key Size (Table 3) Add "T" for 2-piece (078T)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft and Index Unit (Table 4)
Tool Model Number



New Tool Application Form



1. Nut or frangible collar part number _____
2. Hex size of the Nut or frangible collar _____ inches _____ mm
3. What is the final torque requirement of the fastener _____ in-lbs., _____ (Nm)
4. "R" Edge distance between centerline of fastener to nearest structure _____ (in) _____ (mm)
5. "S₁" Total working space _____ (in), _____ (mm)
6. "S₂" Minimum clearance over Pin _____ (in) _____ (mm)
7. Will a hex key be required? YES or NO (circle one), if yes, hex key size _____
8. "A" Offset required, Min _____ Max _____ (inch or mm)
9. Is an extended socket required? Yes or No, Length of socket _____ (inch or mm)
10. "H" Maximum height of the gear head, Including socket _____ (inch or mm)



11. Determine type of tool: Type 1 ____, Type 2 ____, Type 3 ____, Type 4 ____, Type 5 ____
12. Make and model number of preferred nutrunner _____

Company Name _____


Contact _____

Phone _____ FAX _____


Return by FAX: (714) 871-4821 or E-mail glenn.anderson@Arconic.com

Standard & Tall Hex Frangible Collars


**Standard "HL"
Frangible Collar**



**"HST" (Tall Hex)
Frangible Collar**



**"Bi-Hex Nut"
(Airbus)**



Our socket and hex key systems are designed to install all (3) types of fasteners using the same sockets and hex key systems.

Below is an example of a tool ordering number:

CTL1429C343D078
CTL3429A343D078

Bi-Hex Nuts

Example of Fastener Part Numbers:

ASNA2528-(*)


ASNA2536-(*)

ASNA2537-(*)

ASNA2538-(*)

This fastener can be installed as a “frangible collar” using non-torque controlled tools or as a nut installed with torque controlled tools in a pre-torque or final torque condition.

“Bi-Hex Nut”



“Bi-Hex” Nuts have (2) wrenchable hex features. The top hex can be used if you are using a non-torque controlled installation tool. The top hex will “break-off” when the proper seating torque has been reached.


If “Pre-Torquing” the nut is important, tightening the nut without breaking the collar, a deep hex recess socket can be used with a torque controlled tool. The socket reaches over both hex features and the top hex is not removed. This requires a secondary operation to break off the top hex after a period of time.

**Note: “CTL” Frangible collar tool for final installation
“KTLP” indicates a pre-torque tool**

ERGO KEY™ System for Improved Performance & Safety



This unique hex key design keeps it from turning and twisting the return spring during the fastener installation cycle. It also eliminates torsional friction that can build up during installation cycle improving the spring durability and making it easier to remove the tool and move to the next fastener.



High Strength Hex Key System

The purpose of the hex key is to hold the screw or bolt (pin) from turning while the nut is being installed, this is particularly important in non-interference fit holes. It works as a “hold & drive” from the nut side of the application and is affixed to the back of the attached gear housing.

Improved Strength, Solid 1-Piece Hex Key

Solid 1-Pc Hex Key →



1-Piece Hex Key

- Very strong-forged Hex Key
- Available in socket lengths up to 3.0" (76.2mm)
- Hex Keys last longer
- Less downtime
- Improved production
- Easy to change or replace (Does not require tools)
- Lowers fastener install costs
- Available in hex sizes: .062 (1/16"), .078 (5/64), .094 (3/32")

1-Piece Hex Key System



2-Piece Hex Key System



Hex Key




Hex Key Holder with Set Screw

Note: 1-pc and 2-pc hex keys systems are interchangeable


Optional “Quick Change Socket System”

The Arconic tool can be equipped with the “Quick Change” socket feature allowing the operator to easily change the socket and hex key size to install a range of fasteners. Usually one tool has the torque capability to install two or more diameters of collars.

1. Slide the release lever forward, releasing the socket



2. With the release lever forward, a different socket can easily be inserted and is locked in place by pushing the release lever to the locked position.



Standard Arconic 1-Piece Hex Keys

(worn or broken keys are easily changed without special tooling)



Frangible Collar Assembly Tools

Table of Contents

Pistol Grip Power Tools	Section 1
17° Offset Power Tools	Section 2
90° Offset Power Tools	Section 3
90° Right Angle Tools	Section 4
Hand Installation Tools & Hex Key Accessories	Section 5
Collar Removal Tools	Section 6

Sales & Service:

Arconic Fastening Systems
Assembly Tool Systems Division
801 S. Placentia Avenue
Fullerton, CA 92831 USA

714-278-8908 Customer Service
714-871-4821 FAX

Frangible Collar Assembly Tools

Pistol Grip Power Tools

SECTION 1




Frangible Collar Assembly Tools

Pistol Grip Extended Drive Shaft Options

Table 4



Drive Shaft Extended Length

Code	Extended Shaft Length	Index Unit
A	-	With
B	-	Without
C	2.0" (50.8mm)	With
D	2.0" (50.8mm)	Without
G	6.0" (152.4mm)	With
H	6.0" (152.4mm)	Without



Index units are highly recommended, this feature allows the gear head to rotate and lock into place every 45° increasing the utility in various locations.

Offset Pistol Grip Tools



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1428	3	1.25" [31.8mm]	.47" [11.9mm]	.81" [20.5mm]	2.11" [53.5mm]	1.0" [25.4mm]	.35" [8.9mm]

Table 1
Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
437	7/16"

Table 2
Extended Socket Length

Code	Extension
A	Flush
C	3/8"
D	1/2"
E	5/8"
F	3/4"
G	1.0"
J	2.0"

Table 3a
Key Hex Size

Code	Hex Size
062	1/16"
078	5/64"
094	3/32"

Table 3b
Aster™ Key

Code	Dia.
000	No Key
AK2	-2
AK3	-3
AK3A	-3A
AK4	-4


Table 4
Drive Shaft Length with 360° Index Capability

Code	Length	Index Unit
A	-	With
C	2.0"	With
G	6.0"	With

Largest flush socket size is (.312) 5/16" A/F


Example of Complete Tool Model Number:

CTL1428 C 312 E 078




Hex Key Size (Table 3a) or Aster™ Key Size (Table 3b)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft (Table 4)
Tool Model Number

Offset Pistol Grip Tools



Max Torque 140 In-Lbs



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1439	5	2.68" [68.1mm]	.38" [9.5mm]	.69" [17.5mm]	3.53" [89.7mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1
Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
437	7/16"

Table 2
Extended Socket Length

Code	Extension
A	Flush
C	3/8"
D	1/2"
E	5/8"
F	3/4"
G	1.0"
J	2.0"

Table 3a
Key Hex Size

Code	Hex Size
062	1/16"
078	5/64"
094	3/32"

Table 3b
Aster™ Key

Code	Dia.
000	No Key
AK2	-2
AK3	-3
AK3A	-3A
AK4	-4

Table 4
Drive Shaft Length with 360° Index Capability

Code	Length	Index Unit
A	-	With
C	2.0"	With
G	6.0"	With


Maximum Flush Socket is 5/16" (.312) Hex

Example of Complete Tool Model Number:


CTL1439 C 312 E 078

- Hex Key Size (Table 3a) or Aster™ Key Size (Table 3b)
- Extended Socket Length (Table 2)
- Fastener Hex Size (Table 1)
- Ext'd. Drive Shaft (Table 4)
- Tool Model Number

Offset Pistol Grip Tools



Max Torque 140 In-Lb



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1429	5	2.68 [68.1mm]	.47 [11.9mm]	.81 [20.5mm]	3.53 [89.7mm]	1.0 [25.4mm]	.35 [8.8mm]

Table 1

Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
437	7/16"

Table 2

Extended Socket Length

Code	Extension
A	Flush
C	3/8"
D	1/2"
E	5/8"
F	3/4"
G	1.0"
J	2.0"

Table 3a

Key Hex Size

Code	Hex Size
062	1/16"
078	5/64"
094	3/32"

Table 3b

Aster™ Key

Code	Dia.
000	No Key
AK2	-2
AK3	-3
AK3A	-3A
AK4	-4

Table 4

Drive Shaft Length with 360° Index Capability

Code	Length	Index Unit
A	-	With
C	2.0"	With
G	6.0"	With


Maximum Flush Socket is 5/16" (.312) Hex

Example of Complete Tool Model Number:


CTL1429 C 312 E 078

- Hex Key Size (Table 3a) or Aster™ Key Size (Table 3b)
- Extended Socket Length (Table 2)
- Fastener Hex Size (Table 1)
- Ext'd. Drive Shaft (Table 4)
- Tool Model Number

Offset Pistol Grip Tools



Max Torque 140 in-lbs.



Sound level : 78dB(A)

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1438	7	4.13" [104.9mm]	.47" [11.9mm]	.81" [20.5mm]	4.98" [126.5mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


Table 4
Drive Shaft Length
with 360° Index Unit

Code	Length
A	-
C	2.0"
G	6.0"


Largest flush socket size is 5/16" A/F

Example of Complete Tool Model Number:

CTL1438 C 343 D 078



Offset Pistol Grip Tools



Max Torque 80 in_lbs



Model Number	No. of Gears	A	H1	H2	L	R
CTL1408	5	2.38	.34 [8.6mm]	.46	4.18 [106.1mm]	.31 [7.9mm]

Table 1
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"

Table 2
Ext'd.Socket Length

Code	Extension
A	Flush
B	1/4"
C	3/8"
D	1/2"


Table 3a
Key Hex Size

Code	Size
000	No Key
062	1/16"
078	5/64"


Table 3b
Aster™ Key

Code	Dia.
000	No Key
AK2	-2
AK3	-3
AK3A	-3A

Example of Complete Tool Model Number:



Offset Pistol Grip Tools



Max Torque 130 in-lbs.



RPM: 275
Sound level : 78dB

Back Drive Socket Position

Model Number	No. of Gears	A	H ₁	H ₂	L	R
CTL1449	4	1.96 [49.8mm]	.47 [11.8mm]	.81 [20.5mm]	2.81 [71.4mm]	.35 [8.8mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


Table 4
Drive Shaft Length
with 360° Index Unit

Code	Length
A	-
C	2.0"
G	6.0"


Largest flush socket gear size is 5/16" A/F

Example of Complete Tool Model Number:

CTL1449 C 343 D 078



Offset Pistol Grip Tools



Max Torque 140 in-lbs.



RPM: 230
Sound level : 78dB(A)

Back Drive Socket Position

Model Number	No. of Gears	A	H ₁	H ₂	L	R
CTL1715	6	3.38 [85.9mm]	.47 [11.9mm]	.66 [16.7mm]	4.20 [106.7mm]	.33 [8.3mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"

Table 2

Ext'd.Socket Length

Code	Extension
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key

Table 4


Drive Shaft Length
with 360° Index Unit

Code	Length
A	-
C	2.0"
G	6.0"

Largest flush socket gear size is 5/16" A/F


Example of Complete Tool Model Number:

CTL1715 C 312 D 078




Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft (Table 4)
Tool Model Number

Offset Pistol Grip Tools



Max Torque 90 in-lbs.



Shown
without
Index Unit

RPM: 275
Sound level : 78dB(A)

Back Drive Socket Position

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1424	6	3.38" [85.8mm]	.47" [11.9mm]	.81" [20.5mm]	4.05" [102.9mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
A	Flush
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Hex Size
062	1/16"
078	5/64"
094	3/32"

Table 4


Drive Shaft Length
with 360° Index Unit

Code	Length
A	-
C	2.0"
G	6.0"

Largest flush socket gear size is 5/16" A/F


Example of Complete Tool Model Number:

CTL1424 C 312 D 094




Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft (Table 4)
Tool Model Number

Offset Pistol Grip Tools



Max Torque 140 in-lbs.




Model Number	No. of Gears	A	H ₁	H ₂ Ref.	L	W	R
CTL1461	5	2.75" [69.9mm]	.47" [11.9mm]	.81" [20.5mm]	3.68" [93.3mm]	1.0" [25.4mm]	.43" [10.8mm]

Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Key Hex Size		Table 4 Drive Shaft Extended Length		
Code	Hex Size	Code	Extension	Code	Size	Code	Length	Index Unit
219	7/32"	A	Flush	062	1/16" Hex Key	A	-	With
250	1/4"	C	0.375"	078	5/64" Hex Key	B	-	Without
312	5/16"	D	0.500"	094	3/32" Hex Key	C	2.0"	With
343	11/32"	E	0.625"	125T	1/8" Hex Key	D	2.0"	Without
375	3/8"	G	1.0"			G	6.0"	With
437	7/16"	J	2.0"			H	6.0"	Without


24P

Example of Complete Tool Model Number:

CTL1461 C 343 A 078



Offset Pistol Grip Tools



Torque Max: 170 in-lbs



RPM: 220
Sound level : 78dB(A)


Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL1415	3	1.62" [41.1mm]	.68" [17.3mm]	1.0" [25.2mm]	2.69" [68.3mm]	1.0" (25.4mm)	.50" (12.2mm)

The above tool model is designed for use with a flush socket gear or extended sockets.


Table 1 Frangible Collar Hex Size (Across Flats)	Table 2 Ext'd.Socket Length	Table 3 Hex Keys (See Table 5, Accessories)	Table 4 Drive Shaft Extended Length																																															
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr><tr><td>500</td><td>1/2"</td></tr><tr><td>562</td><td>9/16"</td></tr></table>	Code	Hex Size	375	3/8"	437	7/16"	500	1/2"	562	9/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	C	0.375"	D	0.500"	E	0.625"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>094T</td><td>3/32" Hex Key</td></tr><tr><td>125T</td><td>1/8" Dia. Hex Key</td></tr><tr><td>156T</td><td>5/32" Dia. Hex Key</td></tr><tr><td>187T</td><td>3/16" Dia. Hex Key</td></tr></table>	Code	Size	094T	3/32" Hex Key	125T	1/8" Dia. Hex Key	156T	5/32" Dia. Hex Key	187T	3/16" Dia. Hex Key	<table><tr><th>Code</th><th>Length</th><th>Index Unit</th></tr><tr><td>A</td><td>-</td><td>With</td></tr><tr><td>B</td><td>-</td><td>Without</td></tr><tr><td>C</td><td>2.0"</td><td>With</td></tr><tr><td>D</td><td>2.0"</td><td>Without</td></tr></table>	Code	Length	Index Unit	A	-	With	B	-	Without	C	2.0"	With	D	2.0"	Without
Code	Hex Size																																																	
375	3/8"																																																	
437	7/16"																																																	
500	1/2"																																																	
562	9/16"																																																	
Code	Extension																																																	
C	0.375"																																																	
D	0.500"																																																	
E	0.625"																																																	
G	1.0"																																																	
J	2.0"																																																	
Code	Size																																																	
094T	3/32" Hex Key																																																	
125T	1/8" Dia. Hex Key																																																	
156T	5/32" Dia. Hex Key																																																	
187T	3/16" Dia. Hex Key																																																	
Code	Length	Index Unit																																																
A	-	With																																																
B	-	Without																																																
C	2.0"	With																																																
D	2.0"	Without																																																

Example of Complete Tool Model Number:

CTL1415 A 500 G 156T



Offset Pistol Grip Tools




Model Number	No. of Gears	A	H ₁	H ₂ (With Hex Key)	L	W	R
CTL1420	5	3.38" [85.9mm]	.68" [17.3mm]	1.0" [25.4mm]	4.44" [112.7mm]	1.0" (25.4mm)	.50" (12.2mm)

The above tool model is designed for use with a flush socket gear or extended sockets.

Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Hex Keys (See Table 5, Accessories)		Table 4 Drive Shaft Extended Length		
Code	Hex Size	Code	Extension	Code	Size	Code	Length	Index Unit
375	3/8"	C	0.375"	094T	3/32" Hex Key	A	-	With
437	7/16"	D	0.500"	125T	1/8" Dia. Hex Key	B	-	Without
500	1/2"	E	0.625"	156T	5/32" Dia. Hex Key	C	2.0"	With
562	9/16"	G	1.0"	187T	3/16" Dia. Hex Key	D	2.0"	Without
		J	2.0"					


Example of Complete Tool Model Number:

CTL1420 A 500 G 156T



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft (Table 4)
Tool Model Number

Offset Pistol Grip Tools



Torque Max: 210 in-lbs



RPM: 220
Sound level : 78dB(A)


Model Number	No. of Gears	A	H ₁	H ₂ (With Hex Key)	L	W	R
CTL1436	7	5.13" [130.3mm]	.68" [17.3mm]	1.0" [25.4mm]	6.19" [157.3mm]	1.0" (25.4mm)	.50" (12.2mm)

The above tool model is designed for use with a flush socket gear or extended sockets.


Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Hex Keys (See Table 5, Accessories)		Table 4 Drive Shaft Extended Length		
Code	Hex Size	Code	Extension	Code	Size	Code	Length	Index Unit
375	3/8"	C	0.375"	094T	3/32" Hex Key	A	-	With
437	7/16"	D	0.500"	125T	1/8" Dia. Hex Key	B	-	Without
500	1/2"	E	0.625"	156T	5/32" Dia. Hex Key	C	2.0"	With
562	9/16"	G	1.0"	187T	3/16" Dia. Hex Key	D	2.0"	Without
		J	2.0"					

Example of Complete Tool Model Number:

CTL1436 A 500 G 156T



Offset Pistol Grip Tools



Torque Max: 210 in-lbs



Ref: LUM21HR01-K

RPM: 110
Sound level : 78dB(A)


Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTH1415	3	1.62" [41.1mm]	.68" [17.3mm]	1.0" [25.4mm]	2.69" [68.3mm]	1.0" (25.4mm)	.50" (12.2mm)

The above tool model is designed for use with a flush socket gear or extended sockets.


Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Hex Keys (See Table 5, Accessories)		Table 4 Drive Shaft Extended Length		
Code	Hex Size	Code	Extension	Code	Size	Code	Length	Index Unit
375	3/8"	C	0.375"	094T	3/32" Hex Key	A	-	With
437	7/16"	D	0.500"	125T	1/8" Dia. Hex Key	B	-	Without
500	1/2"	E	0.625"	156T	5/32" Dia. Hex Key	C	2.0"	With
562	9/16"	G	1.0"	187T	3/16" Dia. Hex Key	D	2.0"	Without
		J	2.0"					

Example of Complete Tool Model Number:

CTH1415 A 500 G 156T



Offset Pistol Grip Tools



Torque Max: 210 in-lbs

Ref: LUM21HR01-K

RPM: 110

Sound level : 78dB(A)


Model Number	No. of Gears	A	H ₁	H ₂ (With Hex Key)	L	R
CTH1420	5	3.38 [85.9mm]	.68 [17.3mm]	1.0" [25.4mm]	4.44 [113.0mm]	.50 [12.7mm]

The above tool model is designed for use with a flush socket gear or extended sockets.

Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Hex Keys (See Table 5, Accessories)		Table 4 Drive Shaft Extended Length		
Code	Hex Size	Code	Extension	Code	Size	Code	Length	Index Unit
375	3/8"	C	0.375"	094T	3/32" Hex Key	A	-	With
437	7/16"	D	0.500"	125T	1/8" Dia. Hex Key	B	-	Without
500	1/2"	E	0.625"	156T	5/32" Dia. Hex Key	C	2.0"	With
562	9/16"	G	1.0"	187T	3/16" Dia. Hex Key	D	2.0"	Without
		J	2.0"					

Example of Complete Tool Model Number:


CTH1420 A 500 G 156T



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd. Drive Shaft (Table 4)
Tool Model Number

Straight Pistol Grip Tools

Torque Max: 135 in-lbs



RPM at Socket: 290

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
282	9/32"
312	5/16"
343	11/32"

Table 2

Ext'd.Socket Length

Code	Extension
J	2.0"
L	3.0"
P	4.0"


Table 3

Key Hex Size

Code	Size	Part No.
062	1/16"	093-9450-062-CT
078	5/64"	093-9450-078-CT
094	3/32"	093-9450-094-CT


Example of Complete Tool Model Number:

CTL2028B 343 J 094



Straight Pistol Grip Tools

Torque Max: 160 in-lbs



RPM at Socket: 290

Table 1

Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
282	9/32"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
J	2.0"
L	3.0"
P	4.0"


Table 3

Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key

Example of Complete Tool Model Number:

CT2005B 437 J 094



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number


Frangible Collar Assembly Tools

17° Offset Power Tools

SECTION 2



17° Offset Lever Tools



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3428	3	1.25" [31.8mm]	.47" [11.9mm]	.81" [20.5mm]	2.11" [53.5mm]	1.0" [25.4mm]	.35" [8.9mm]

The above model tools are designed for use with extended sockets.

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"

Table 2
Ext'd.Socket Length

Code	Extension
A	Flush
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3
Key Hex Size


Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key

* Flush sockets only available in (.219, .250) hex sizes

24P


Example of Complete Tool Model Number:

CTL3428A 343 G 078



17° Offset Lever Tools

Torque Max: 145 in-lbs



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3429A	5	2.68" [68.1mm]	.47" [11.9mm]	.81" [20.5mm]	3.53" [89.7mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
A *	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


* Flush sockets only available in (.219, .250, .282, .312) hex sizes

Example of Complete Tool Model Number:

CTL3429A 343 F 078

- Hex Key Size (Table 3)
- Extended Socket Length (Table 2)
- Fastener Hex Size (Table 1)
- Tool Model Number

17° Offset Lever Tools



Torque Max: 120 in-lbs



RPM at Socket: 275

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3438	7	4.13" [104.9mm]	.47" [11.9mm]	.81" [20.5mm]	4.98" [126.5mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
A*	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


* Flush sockets available in (.250, .282 & .312) hex sizes

Example of Complete Tool Model Number:


CTL3438A 343 F 078

CTL3438A 343 F 078
 └──────────┬──────────┬──────────┬──────────
 Tool Model Number Fastener Hex Size (Table 1) Extended Socket Length (Table 2) Hex Key Size (Table 3)

17° Offset Lever Tools



Torque Max: 120 in-lbs



RPM at Socket: 275

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3424A	6	3.38" [85.8mm]	.47" [11.9mm]	.81" [20.5mm]	4.05" [102.9mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
A *	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"


Table 3
Key Hex Size

Code	Hex Size
062	1/16"
078	5/64"
094	3/32"


* Flush sockets available in (.220, .250, .282 & .312) hex sizes

Example of Complete Tool Model Number:

CTL3424A 343 F 078



17° Offset Lever Tools



Torque Max: 80 in-lbs



Model Number	No. of Gears	A	H1	H2	L	R
CTL3421	5	2.38	.34 [8.6mm]	.46	4.18 [106.1mm]	.31 [7.9mm]

Table 1
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"

Table 2
Ext'd.Socket Length

Code	Extension
A	Flush
B	1/4"
C	3/8"
D	1/2"

Table 3a
Key Hex Size

Code	Size
000	No Key
062	1/16"
078	5/64"

Table 3b
Aster™Key


Code	Dia.
000	No Key
AK2	-2
AK3	-3
AK3A	-3A

Example of Complete Tool Model Number:

CTL3421A 312 D 000

CTL3421A — Tool Model Number
 312 — Fastener Hex Size (Table 1)
 D — Extended Socket Length (Table 2)
 000 — Hex Key Size (Table 3a or 3b)

17° Offset Lever Tools



Torque Max: 90 in-lbs



Model Number	No. of Gears	A	H ₁	L	R
CTL3707A	5	1.97" [50.0mm]	.285" [7.2mm]	2.65" [67.3mm]	.30" [7.6mm]
CTL3777A	7	2.97" [75.4mm]	.285" [7.2mm]	3.81" [96.8mm]	.30" [7.6mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"

Table 2

Ext'd.Socket
Length

Code	Extension
A	Flush Sockets Only

Table 3

Key Hex Size

Code	Hex Size
000	NA
062	1/16"
078	5/64"

This tool model is not recommended for use with extended sockets, please select another model if an extended socket is required.


Example of Complete Tool Model Number:

CTL3707A 343 A 078

Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

17° Offset Lever Tools

Torque Max: 145 in-lbs



RPM at Socket: 260

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3439A	5	2.68" [68.1mm]	.38" [9.5mm]	.69" [17.5mm]	3.53" [89.7mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
A *	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


* Flush sockets only available in (.219, .250, .282, .312) hex sizes

Example of Complete Tool Model Number:

CTL3439A 437 D 094

CTL3439A — Tool Model Number
 437 — Fastener Hex Size (Table 1)
 D — Extended Socket Length (Table 2)
 094 — Hex Key Size (Table 3)

17° Offset Lever Tools



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3452A	5	2.72" [69.1mm]	.47" [11.9mm]	.81" [20.5mm]	3.70" [94.0mm]	1.0" [25.4mm]	.39" [9.7mm]

Table 1	Table 2	Table 3	Table 3																																																
Collar Hex Size	Ext'd.Socket Length	Key Hex Size	Aster™ Key																																																
<table><tr><th>Code</th><th>Dia.</th></tr><tr><td>219</td><td>-2</td></tr><tr><td>250</td><td>-3</td></tr><tr><td>282</td><td>-3A</td></tr><tr><td>312</td><td>-4</td></tr></table>	Code	Dia.	219	-2	250	-3	282	-3A	312	-4	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A *</td><td>Flush</td></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>F</td><td>0.750"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A *	Flush	C	0.375"	D	0.500"	E	0.625"	F	0.750"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>062</td><td>1/16" Hex Key</td></tr><tr><td>078</td><td>5/64" Hex Key</td></tr><tr><td>094</td><td>3/32" Hex Key</td></tr><tr><td></td><td></td></tr></table>	Code	Size	062	1/16" Hex Key	078	5/64" Hex Key	094	3/32" Hex Key			<table><tr><th>Code</th><th>Dia.</th></tr><tr><td>000</td><td>No Key</td></tr><tr><td>AK2</td><td>-2</td></tr><tr><td>AK3</td><td>-3</td></tr><tr><td>AK3A</td><td>-3A</td></tr><tr><td>AK4</td><td>-4</td></tr></table>	Code	Dia.	000	No Key	AK2	-2	AK3	-3	AK3A	-3A	AK4	-4
Code	Dia.																																																		
219	-2																																																		
250	-3																																																		
282	-3A																																																		
312	-4																																																		
Code	Extension																																																		
A *	Flush																																																		
C	0.375"																																																		
D	0.500"																																																		
E	0.625"																																																		
F	0.750"																																																		
G	1.0"																																																		
J	2.0"																																																		
Code	Size																																																		
062	1/16" Hex Key																																																		
078	5/64" Hex Key																																																		
094	3/32" Hex Key																																																		
Code	Dia.																																																		
000	No Key																																																		
AK2	-2																																																		
AK3	-3																																																		
AK3A	-3A																																																		
AK4	-4																																																		

* Flush sockets only available in (.219, .250, .223, .312) hex sizes



24P

Example of Complete Tool Model Number:

CTL3452A 312 F 094

CTL3452A — Tool Model Number
 312 — Fastener Hex Size (Table 1)
 F — Extended Socket Length (Table 2)
 094 — Hex Key or Aster™ Key Option (Table 3)

17° Offset Lever Tools



Torque Max: 150 in-lbs

RPM at Socket: 270

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3402A	5	2.75" [69.9mm]	.38" [9.71mm]	.73" [18.5mm]	3.68" [93.3mm]	1.0" [25.4mm]	.43" [10.8mm]

The above model tools are designed for use with a flush socket gear or extended sockets.

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
A	Flush
C	0.375"
D	0.500"
E	0.625"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
078	5/64" Hex Key
094	3/32" Hex Key
125T	1/8" Hex Key


1/8" Hex key available on
Models CT3110 and CT3111

Example of Complete Tool Model Number:

CTL3402A 343 A 078

- Hex Key Size (Table 3)
- Extended Socket Length (Table 2)
- Fastener Hex Size (Table 1)
- Tool Model Number

17° Offset Lever Tools



Torque Max: 150 in-lbs
RPM at Socket: 270



“Flush or Extended
Socket Applications”

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL3111A	5	2.75" [69.9mm]	.47" [11.9mm]	.78" [19.8mm]	3.68" [93.3mm]	1.0" [25.4mm]	.43" [10.8mm]

The above model tools are designed for use with a flush socket gear or extended sockets.


Table 1 Frangible Collar Hex Size (Across Flats)	Table 2 Ext'd.Socket Length	Table 3 Key Hex Size																																				
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>219</td><td>7/32"</td></tr><tr><td>250</td><td>1/4"</td></tr><tr><td>312</td><td>5/16"</td></tr><tr><td>343</td><td>11/32"</td></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr></table>	Code	Hex Size	219	7/32"	250	1/4"	312	5/16"	343	11/32"	375	3/8"	437	7/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A</td><td>Flush</td></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A	Flush	C	0.375"	D	0.500"	E	0.625"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>078T</td><td>5/64" Hex Key</td></tr><tr><td>094T</td><td>3/32" Hex Key</td></tr><tr><td>125T</td><td>1/8" Hex Key</td></tr></table>	Code	Size	078T	5/64" Hex Key	094T	3/32" Hex Key	125T	1/8" Hex Key
Code	Hex Size																																					
219	7/32"																																					
250	1/4"																																					
312	5/16"																																					
343	11/32"																																					
375	3/8"																																					
437	7/16"																																					
Code	Extension																																					
A	Flush																																					
C	0.375"																																					
D	0.500"																																					
E	0.625"																																					
G	1.0"																																					
J	2.0"																																					
Code	Size																																					
078T	5/64" Hex Key																																					
094T	3/32" Hex Key																																					
125T	1/8" Hex Key																																					

Example of Complete Tool Model Number:

CTL3111 C 343 A 078

CTL3111: Tool Model Number
 C: Ext'd. Drive Shaft (Table 4)
 343: Fastener Hex Size (Table 1)
 A: Extended Socket Length (Table 2)
 078: Hex Key Size (Table 3)

17° Offset Lever Tools



Torque Max: 230 in-lbs

Motor: LBB16S005 Mod.



RPM: 220 at socket

Model Number	No. of Gears	A	H ₁	H ₂ (Ref)	L	W	R
CTL3498A	5	3.19 [81.0mm]	.50 [11.4mm]	.84 [21.5mm]	4.5 [114.3mm]	1.12 [28.4mm]	.43 [10.8mm]

This is a very durable tool design for general purpose applications and is designed for use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1

Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
375	3/8"
437	7/16"
500	1/2"
562	9/16"

Table 2

Ext'd.Socket Length

Code	Extension
A	Flush
E	0.625"
F	0.750"
G	1.0"

Table 3


Key Hex Size

Code	Size
094	3/32" Hex Key
125T	1/8" Hex Key

Max flush hex size is 1/2" A/F


Example of Complete Tool Model Number:

CTL3498A 437 A 125T



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

17° Offset Lever Tools



Torque Max: 310 in-lbs



Ref: LTV28N30-10 Mod.

Model Number	No. of Gears	A	H ₁	H ₂	L	R	W
CT3475A	5	3.23" [82.0mm]	.50" [12.7mm]	.84" [21.5mm]	4.3" [109.2mm]	.50" [12.7mm]	1.0" [25.4mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
437	7/16"
500	1/2"
562	9/16"

Table 2

Ext'd. Socket Length

Code	Extension
A	Flush
E	5/8"
G	1.0"
J	2.0"


Table 3

Key Hex Size


Code	Size
000	NA
125T	1/8"
156T	5/32"

.500 Max A/F Flush Socket Gear

Example of Complete Tool Model Number:



17° Offset Lever Tools



Torque Max: 320 in-lbs



Ref: LTV28N30-10 Mod.

RPM at Socket: 175

Model Number	No. of Gears	A	H ₁	H ₂	L	R	W
CTL3472A	5	3.0" [76.2mm]	.69" [17.5mm]	1.0" [25.4mm]	4.2" [106.4mm]	.56" [14.2mm]	1.12" [28.4mm]

Model CTL3472A is designed for use with a flush socket gear or extended sockets

Table 1 Frangible Collar Hex Size (Across Flats)	Table 2 Ext'd.Socket Length	Table 3 Key Hex Size																																						
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr><tr><td>500</td><td>1/2"</td></tr><tr><td>562</td><td>9/16"</td></tr><tr><td>625</td><td>5/8"</td></tr><tr><td>687</td><td>11/16"</td></tr></table>	Code	Hex Size	375	3/8"	437	7/16"	500	1/2"	562	9/16"	625	5/8"	687	11/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A</td><td>Flush</td></tr><tr><td>E</td><td>5/8"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A	Flush	E	5/8"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>000</td><td>NA</td></tr><tr><td>125T</td><td>1/8"</td></tr><tr><td>156T</td><td>5/32"</td></tr><tr><td>187T</td><td>3/16"</td></tr><tr><td>219T</td><td>7/32"</td></tr><tr><td>250T</td><td>1/4"</td></tr></table>	Code	Size	000	NA	125T	1/8"	156T	5/32"	187T	3/16"	219T	7/32"	250T	1/4"
Code	Hex Size																																							
375	3/8"																																							
437	7/16"																																							
500	1/2"																																							
562	9/16"																																							
625	5/8"																																							
687	11/16"																																							
Code	Extension																																							
A	Flush																																							
E	5/8"																																							
G	1.0"																																							
J	2.0"																																							
Code	Size																																							
000	NA																																							
125T	1/8"																																							
156T	5/32"																																							
187T	3/16"																																							
219T	7/32"																																							
250T	1/4"																																							

.687 Max A/F Flush Socket Gear


.687 Max A/F Flush Socket Gear

Example of Complete Tool Model Number:

CTL3472 A 625 D 156T

CTL3472: Tool Model Number
 A: With 360° Index Unit
 625: Fastener Diameter (Table 1)
 D: Extended Socket Length (Table 2)
 156T: Ergo Hex Key Size (Table 3)

17° Offset Lever Tools



Torque Max: 520 in-lbs



Ref: LTV38N68-13 Mod.

RPM at Socket: 100

Model Number	No. of Gears	A	H ₁	H ₂ (Ref)	L	W	R
CT3472A	5	3.00" [76.2mm]	.69" [17.5mm]	1.0" [25.4mm]	4.2" [106.4mm]	1.12" [28.4mm]	.56" [14.2mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
437	7/16"
500	1/2"
562	9/16"
625	5/8"
687	11/16"
750	3/4"

Table 2

Ext'd.Socket Length

Code	Extension
A	Flush
E	5/8"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size
000	NA
125T	1/8"
156T	5/32"
187T	3/16"
219T	7/32"
250T	1/4"

.687 Max A/F Flush Socket Gear

Example of Complete Tool Model Number:

CT3472 A 625 D 156T

Ergo Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Diameter (Table 1)
With 360° Index Unit
Tool Model Number


Frangible Collars Assembly Tools

90° Offset Power Tools

SECTION 3



90° Offset Lever Tools



Torque Max: 140 in-lbs



250 RPM at Socket

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL5428A	3	1.25" [31.8mm]	.47" [11.9mm]	.81" [20.5mm]	2.1" [53.3mm]	1.0" [25.4mm]	.35" [8.8mm]

This is a very durable tool design for general purpose applications and is designed for use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1

Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
282	9/32"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
A *	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size	Hex Key P/N
062T	1/16" 2-Pc Hex Key	093-9337
078T	5/64" 2-Pc Hex Key	093-9334
094T	3/32" 2-Pc Hex Key	093-9333

062	1/16" 1-Pc Hex Key	Depends on socket length
078	5/64" 1-Pc Hex Key	
094	3/32" 1-Pc Hex Key	

* Flush sockets only available in (.219, .250, .282, .312) hex sizes


24P

* Flush sockets only available in (.219, .250, .282, .312) hex sizes

24P

Example of Complete Tool Model Number:


CTL5428A 250 C 078



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

90° Offset Lever Tools

Torque Max: 145 in-lbs



RPM at Socket: 260

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL5439A	5	2.68" [68.1mm]	.38" [9.5mm]	.69" [17.5mm]	3.53" [89.7mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
A *	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key


* Flush sockets only available in (.219, .250, .282, .312) hex sizes

Example of Complete Tool Model Number:

CTL5439A 437 D 094

CTL5439A — Tool Model Number
 437 — Fastener Hex Size (Table 1)
 D — Extended Socket Length (Table 2)
 094 — Hex Key Size (Table 3)

90° Offset Lever Tools



Torque Max: 140 in-lbs



Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL5429A	5	2.68" [68.1mm]	.47" [11.9mm]	.81" [20.5mm]	3.53" [89.7mm]	1.0" [25.4mm]	.35" [8.8mm]


Table 1 Frangible Collar Hex Size (Across Flats)	Table 2 Ext'd.Socket Length	Table 3 Key Hex Size																																										
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>219</td><td>7/32"</td></tr><tr><td>250</td><td>1/4"</td></tr><tr><td>282</td><td>9/32"</td></tr><tr><td>312</td><td>5/16"</td></tr><tr><td>343</td><td>11/32"</td></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr></table>	Code	Hex Size	219	7/32"	250	1/4"	282	9/32"	312	5/16"	343	11/32"	375	3/8"	437	7/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A*</td><td>Flush</td></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>F</td><td>0.750"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A*	Flush	C	0.375"	D	0.500"	E	0.625"	F	0.750"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>062</td><td>1/16" Hex Key</td></tr><tr><td>078</td><td>5/64" Hex Key</td></tr><tr><td>094</td><td>3/32" Hex Key</td></tr><tr><td></td><td></td></tr></table>	Code	Size	062	1/16" Hex Key	078	5/64" Hex Key	094	3/32" Hex Key		
Code	Hex Size																																											
219	7/32"																																											
250	1/4"																																											
282	9/32"																																											
312	5/16"																																											
343	11/32"																																											
375	3/8"																																											
437	7/16"																																											
Code	Extension																																											
A*	Flush																																											
C	0.375"																																											
D	0.500"																																											
E	0.625"																																											
F	0.750"																																											
G	1.0"																																											
J	2.0"																																											
Code	Size																																											
062	1/16" Hex Key																																											
078	5/64" Hex Key																																											
094	3/32" Hex Key																																											
* Flush sockets only available in (.219, .250, .282, .312) hex sizes																																												

24P


24P

Example of Complete Tool Model Number:

CTL5429A 437 F 094



90° Offset Lever Tools



150 in lbs Max.



Model Number	No. of Gears	A	H ₁	H ₂	L	R
CTL5461A	5	2.75 [69.9mm]	.47 [11.9mm]	.61 [15.4mm]	3.68 [93.3mm]	.43 [10.8mm]

This is a very durable tool design for general purpose applications and is designed for use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1	Table 2	Table 3																																										
Frangible Collar	Ext'd.Socket Length	Key Hex Size																																										
Hex Size (Across Flats)																																												
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>219</td><td>7/32"</td></tr><tr><td>250</td><td>1/4"</td></tr><tr><td>282</td><td>9/32"</td></tr><tr><td>312</td><td>5/16"</td></tr><tr><td>343</td><td>11/32"</td></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr></table>	Code	Hex Size	219	7/32"	250	1/4"	282	9/32"	312	5/16"	343	11/32"	375	3/8"	437	7/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A *</td><td>Flush</td></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>F</td><td>0.750"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A *	Flush	C	0.375"	D	0.500"	E	0.625"	F	0.750"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>062</td><td>1/16" Hex Key</td></tr><tr><td>078</td><td>5/64" Hex Key</td></tr><tr><td>094</td><td>3/32" Hex Key</td></tr><tr><td>125T</td><td>1/8" Hex Key</td></tr></table>	Code	Size	062	1/16" Hex Key	078	5/64" Hex Key	094	3/32" Hex Key	125T	1/8" Hex Key
Code	Hex Size																																											
219	7/32"																																											
250	1/4"																																											
282	9/32"																																											
312	5/16"																																											
343	11/32"																																											
375	3/8"																																											
437	7/16"																																											
Code	Extension																																											
A *	Flush																																											
C	0.375"																																											
D	0.500"																																											
E	0.625"																																											
F	0.750"																																											
G	1.0"																																											
J	2.0"																																											
Code	Size																																											
062	1/16" Hex Key																																											
078	5/64" Hex Key																																											
094	3/32" Hex Key																																											
125T	1/8" Hex Key																																											


* Flush sockets only available in (.219, .250, .282, .312) hex sizes

Example of Complete Tool Model Number:

CTL5461A 312 C 078

Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

90° Offset Lever Tools



150 in lbs Max.



Model Number	No. of Gears	A	H ₁	H ₂	L	R
CTL5111A	5	2.75 [69.9mm]	.47 [11.9mm]	.61 [15.4mm]	3.68 [93.3mm]	.43 [10.8mm]

This is a very durable tool design for general purpose applications and is designed for use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1	Table 2	Table 3																																										
Frangible Collar	Ext'd.Socket Length	Key Hex Size																																										
Hex Size (Across Flats)																																												
<table><tr><th>Code</th><th>Hex Size</th></tr><tr><td>219</td><td>7/32"</td></tr><tr><td>250</td><td>1/4"</td></tr><tr><td>282</td><td>9/32"</td></tr><tr><td>312</td><td>5/16"</td></tr><tr><td>343</td><td>11/32"</td></tr><tr><td>375</td><td>3/8"</td></tr><tr><td>437</td><td>7/16"</td></tr></table>	Code	Hex Size	219	7/32"	250	1/4"	282	9/32"	312	5/16"	343	11/32"	375	3/8"	437	7/16"	<table><tr><th>Code</th><th>Extension</th></tr><tr><td>A *</td><td>Flush</td></tr><tr><td>C</td><td>0.375"</td></tr><tr><td>D</td><td>0.500"</td></tr><tr><td>E</td><td>0.625"</td></tr><tr><td>F</td><td>0.750"</td></tr><tr><td>G</td><td>1.0"</td></tr><tr><td>J</td><td>2.0"</td></tr></table>	Code	Extension	A *	Flush	C	0.375"	D	0.500"	E	0.625"	F	0.750"	G	1.0"	J	2.0"	<table><tr><th>Code</th><th>Size</th></tr><tr><td>062T</td><td>1/16" Hex Key</td></tr><tr><td>078T</td><td>5/64" Hex Key</td></tr><tr><td>094T</td><td>3/32" Hex Key</td></tr><tr><td>125T</td><td>1/8" Hex Key</td></tr></table>	Code	Size	062T	1/16" Hex Key	078T	5/64" Hex Key	094T	3/32" Hex Key	125T	1/8" Hex Key
Code	Hex Size																																											
219	7/32"																																											
250	1/4"																																											
282	9/32"																																											
312	5/16"																																											
343	11/32"																																											
375	3/8"																																											
437	7/16"																																											
Code	Extension																																											
A *	Flush																																											
C	0.375"																																											
D	0.500"																																											
E	0.625"																																											
F	0.750"																																											
G	1.0"																																											
J	2.0"																																											
Code	Size																																											
062T	1/16" Hex Key																																											
078T	5/64" Hex Key																																											
094T	3/32" Hex Key																																											
125T	1/8" Hex Key																																											

* Flush sockets only available in (.219, .250, .282, .312) hex sizes

24P

* Flush sockets only available in (.219, .250, .282, .312) hex sizes


24P

Example of Complete Tool Model Number:

CTL5111 C 343 A 078

CTL5111
 C
 343
 A
 078
 Hex Key Size (Table 3)
 Extended Socket Length (Table 2)
 Fastener Hex Size (Table 1)
 Ext'd. Drive Shaft (Table 4)
 Tool Model Number

90° Offset Lever Tools



Torque Max: 140 in-lbs



360° Index Unit

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL5438	7	4.13" [104.9mm]	.47" [11.9mm]	.81" [20.5mm]	4.98" [126.5mm]	1.0" [25.4mm]	.35" [8.8mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
282	9/32"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2

Ext'd.Socket Length

Code	Extension
A*	Flush
C	0.375"
D	0.500"
E	0.625"
F	0.750"
G	1.0"
J	2.0"

Table 3


Key Hex Size

Code	Size
062	1/16" Hex Key
078	5/64" Hex Key
094	3/32" Hex Key

* Flush sockets only available in (.219, .250, .282, .312) hex sizes


Example of Complete Tool Model Number:

CTL5438A 437 F 094



Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

90° Offset Lever Tools




Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CTL5498A	5	3.19" [81.0mm]	.50" [12.7mm]	.84" [21.5mm]	4.5" [114.3mm]	1.12" [28.4mm]	.43" [10.8mm]

This is a very durable tool design for general purpose applications and is designed for use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1 Frangible Collar Hex Size (Across Flats)		Table 2 Ext'd.Socket Length		Table 3 Key Hex Size	
Code	Hex Size	Code	Extension	Code	Size
375	3/8"	A	Flush	094	3/32" Hex Key
437	7/16"	D	0.500"	125T	1/8" Hex Key
500	1/2"	E	0.625"	156T	5/32" Hex Key
562	9/16"	F	0.750"		
		G	1.0"		


Example of Complete Tool Model Number:



90° Offset Lever Tools

Page 1 of 2

130 in lbs Max



Model Number	No. of Gears	A	H ₁	H ₂	L	R	W (Front)
CT5705	9	6.59" [167.4mm]	.43" [10.9mm]	.73" [18.5mm]	7.6" [193mm]	.35" [8.9mm]	1.0" [25.4mm]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
A	Flush
C	3/8"
D	1/2"
E	5/8"
G	1.0"
J	2.0"

Table 3
Key Hex Size

Code	Size
078	5/64" Hex Key
094	3/32" Hex Key

Table 4
Extended Drive
Shaft with 360°
Index Capability

Code	Extension
A	1-1/2"
E	4.0"
G	6.0"
K	12.0"


Example of Complete Tool Model Number:

CT5705 G 437 F 094

Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Ext'd Drive Shaft-Index (Table 4)
Tool Model Number

90° Offset Lever Tools

300 in-lbs



Ref: LTV28N28-10

RPM at Socket: 270


Model Number	No. of Gears	A	H ₁	H ₂	L	R	W
CTL5472A	5	3.0" [76.2mm]	.69" [17.5mm]	1.0" [25.4mm]	4.19" [106.4mm]	.56" [14.2mm]	1.12" [28.4mm]

This is a very durable tool design for general purpose applications and is designed for Use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.


</

Example of Complete Tool Model Number:



90° Offset Lever Tools

450 in-lbs



Ref: LTV38N68-13

RPM at Socket: 290

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CT5720A	7	3.69" [93.6mm]	.69" [17.5mm]	1.0" [25.4mm]	4.88" [124.0mm]	1.12" [28.4mm]	.56" [14.2mm]

This is a very durable tool design for general purpose applications and is designed for Use in a flush condition or with extended sockets and hex keys when required.

This gear head has 360° indexing capability.

Table 1

Frangible Collar

Hex Size (Across Flats)

Code	Hex Size
437	7/16"
500	1/2"
562	9/16"
625	5/8"

Table 2

Ext'd. Socket Length

Code	Extension
A	Flush
E	5/8"
G	1.0"
J	2.0"

Table 3

Key Hex Size

Code	Size
000	NA
156T	5/32"
187T	3/16"

.625 Max A/F Flush Socket Gear

Example of Complete Tool Model Number:

CT5720A 500 A 156T

Hex Key Size (Table 3)


Extended Socket Length (Table 2)

Fastener Hex Size (Table 1)

Tool Model Number

90° Offset Lever Tools

Torque Max: 840 in-lbs



Pictured Tool is a Simulation of actual tool model

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CT5605	3	2.18" [55.25mm]	.77" [19.5mm]	1.12" [28.4mm]	4.55" [115.57mm]	1.38" [35.1mm]	.69" [17.5mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
562	9/16"
625	5/8"
687	11/16"
750	3/4"
875	7/8"

Table 2

Ext'd. Socket Length

Code	Extension
A	Flush
E	5/8"
G	1.0"
H	1.5"
J	2.0"

Table 3

Key Hex Size

Code	Size
000	NA
156T	5/32"
187T	3/16"
219T	7/32"
250T	1/4"

.626 Max A/F Flush Socket Gear


Example of Complete Tool Model Number:

CT(D)5605A 625 A 187T



90° Offset Lever Tools

Torque Max: 1290 in-lbs



Pictured Tool is a Simulation of actual tool model



Head Only

Model Number	No. of Gears	A	H ₁	H ₂	L	W	R
CT5723B	3	2.88" [73.2mm]	1.0" [25.4mm]	1.18" [29.9mm]	4.85" [123.2mm]	1.80" [45.7mm]	.90" [22.8mm]

Table 1

Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
750	3/4"
875	7/8"
937	15/16"

Table 2

Ext'd.Socket Length

Code	Extension
A	Flush
E	5/8"
G	1.0"
H	1.5"
J	2.0"

Table 3

Key Hex Size

Code	Size
000	NA
219T	7/32"
250T	1/4"

.626 Max A/F Flush Socket Gear

Example of Complete Tool Model Number:

CT5723B 750 F 219T

_____ Hex or Aster™ Key Size (Table 3a or 3b)
 _____ Extended Socket Length (Table 2)
 _____ Fastener Hex Size (Table 1)
 _____ Tool Model Number

Frangible Collars Assembly Tools

90° Right Angle Power Tools

SECTION 4



90° Angle Head Tools

Max Torque 220 in-lbs



RPM at Socket: 275

Model Number	L	H	Center to Side Angle Head	Weight
CT310AA	9.6" [243mm]	1.5" [36.6mm]	0.53" [13.5mm]	1.9 lbs [0.88 kg]

Table 1
Frangible Collar
Hex Size (Across Flats)

Code	Hex Size
219	7/32"
250	1/4"
282	9/32"
312	5/16"
343	11/32"
375	3/8"
437	7/16"

Table 2
Ext'd.Socket Length

Code	Extension
F	0.750"
G	1.0"
J	2.0"
L	3.0"

Table 3
Key Hex Size

Code	Size
062T	1/16" Hex Key
078T	5/64" Hex Key
094T	3/32" Hex Key

Example of Complete Tool Model Number:

CT310AA 312 J 078T

Hex Key Size (Table 3)
Extended Socket Length (Table 2)
Fastener Hex Size (Table 1)
Tool Model Number

90° Angle Head Tools




Table 1

Tool Model Number	Max Torque (in-lbs)	Max Torque Nm	RPM	Hex Socket Sizes (A/F)								Hex Key Sizes		
CT310AA	220	15	275	7/32	1/4	9/32	5/16	11/32				.062	.078	.094
CT310AB	265	30	400	5/16	11/32	7/16	1/2	9/16				.094	.125	.156
CT310AD	480	55	370	7/16	1/2	9/16	5/8	11/16	3/4			.125	.156	.187
CT310AE	600	68	370	7/16	1/2	9/16	5/8	11/16	3/4			.125	.156	.187
CT310AF	750	85	300	1/2	9/16	5/8	11/16	3/4	7/8			.156	.187	.219
CT310BJ	1050	120	215	5/8	11/16	3/4	7/8	15/16	1.0	1 1/8	1 1/4	.187	.219	.250
CT310BK	1330	150	170	5/8	11/16	3/4	7/8	15/16	1.0	1 1/8	1 1/4	.219	.250	
CT310AN	1775	200	320	5/8	11/16	3/4	7/8	15/16	1.0	1 1/8	1 1/4	.219	.250	
CT310AP	3100	350	240	5/8	11/16	3/4	7/8	15/16	1.0	1 1/8	1 1/4	.250		
CT310AQ	5100	575	180	5/8	11/16	3/4	7/8	15/16	1.0	1 1/8	1 1/4	.250		

Example of Complete Tool Model Number:

CT310AG 750 G 187T



Hex Key Size (Table 1)
Extended Socket Length (Table 2)
Hex Socket Size (Table 1)
Tool Model Number

Table 2

Ext'd. Socket Length

Code	Extension
B	.250 "
D	.500 "
E	.625 "
G	1.0"
J	2.0"
L	3.0"

90° Angle Head Tools

Installation Hand Tools and Hex Keys Accessories

SECTION 5



Hand Assembly Tools For Frangible Collars

Small Roller Wrenches, 40 & 80 in-lbs




Roller Wrenches With Square Drive

Part Number	Max Torque	Socket Drive	Hole Thru Dia.
RWB100-40	40 in-lbs	1/4"	.119
RWB100-80	80 in-lbs	1/4"	.119
RWBO100-40	40 in-lbs	1/4"	.119
RWBO100-80	80 in-lbs	1/4"	.119

Hand Assembly Tools For Frangible Collars

Medium Roller Wrench with 3/8" Sq. Drive




Roller Wrench With Square Drive

Ordering Number	Max Torque	Socket Sq. Drive	Hole Thru Dia.
RWB100-150-375	150 in-lbs	3/8"	.231 .236

Hand Assembly Tools For Frangible Collars

Medium Roller Wrench with Integrated Sockets




Ordering Number	Hex Size		L	Hole Thru Dia.
RWB130A-31	.312	5/16"	.250	.166
RWB130A-34	.343	11/32"	.270	.166
RWB130A-37	.375	3/8"	.370	.166
RWB130A-43	.437	7/16"	.430	.166

- Designed to fit into limited access applications
- Will install frangible collars requiring 150 in-lbs [17Nm] of applied torque

Hand Assembly Tools For Frangible Collars

Lt. Duty Roller Wrenches with Integrated Sockets




Ordering Number	(H) Hex Size		L	Hole Thru Dia.
RWB40A-21	.219	7/32"	.240	7/32"
RWB40A-25	.250	1/4"	.240	7/32"
RWB40A-28	.281	9/32"	.240	7/32"
RWB40A-31	.312	5/16"	.250	7/32"
RWB40A-34	.343	11/32"	.270	7/32"

- Maximum 40 in-lbs Torque Capability
- Designed to fit into limited access applications
- Do not exceed maximum torque capability of the roller wrench

Hand Assembly Tools For Frangible Collars

Lt. Duty Roller Wrenches with Integrated Sockets



Ordering Number	(H) Hex Size		L	Hole Thru Dia.
RWB80A-21	.219	7/32"	.240	7/32"
RWB80A-25	.250	1/4"	.240	7/32"
RWB80A-28	.281	9/32"	.240	7/32"
RWB80A-31	.312	5/16"	.250	7/32"
RWB80A-34	.343	11/32"	.270	7/32"

- Maximum 80 in-lbs Torque Capability
- Designed to fit into limited access applications
- Do not exceed maximum torque capability of the roller wrench

Hand Assembly Tools For Frangible Collars

Roller Wrench, up to 400 in-lbs



Ordering Number	A Ref.	Handle Length Ref.	C Dia. Ref.	D Max.	Square Drive	Hole Thru Dia.
RWB100-400	2.0	8.0	1.5	.74	3/8"	1/8"

- Notes:
- 1. Sockets are not included with the Roller Wrench
 - 2. Hex Key Handle Assembly sold separately

Hand Assembly Tools For Frangible Collars

Roller Wrench, up to 400 in-lbs




Ordering Number	Hex Size	A Length Ref.	B Height Ref.	C Radius Max.	D Dia. Ref.	Handle Length Ref.	Hole Thru Dia.	Square Drive
RWB100-400-37	.375	1.25	.785	.74	1.5	8.0	1/8"	3/8"
RWB100-400-50	.500	1.25	.785	.74	1.5	8.0	1/8"	3/8"
RWB100-400-56	.562	1.25	.785	.74	1.5	8.0	1/8"	3/8"

- Notes:
- 1. Socket is included with this Roller Wrench
 - 2. Hex Key Handle Assembly sold separately

Hand Assembly Tools For Frangible Collars

SPKH –Special Hex Key Handle



Hex Keys


Pin Dia.	Handle (20°)	Handle (Straight)	Hex Key Size	Hex Keys Choices	
				.825 Long	2.5" Long
-5	SPKH-6	SPKH-6S	.078 (5/64")	093-9322	093-9323
-6	SPKH-6	SPKH-6S	.078 (5/64")	093-9322	093-9323
-8	SPKH-8	SPKH-8S	.094 (3/32")	093-9324	093-9325
-10	SPKH-10	SPKH-10S	.125 (1/8")	016-9867	016-9868
-12	SPKH-12	SPKH-12S	.156 (5/32")	016-9869	016-9870
-14	SPKH-14	SPKH-14S	.187 (3/16")	216-9008	216-9009

How to Order:

1. Order Handle Assembly Separately: SPKH-(*)
2. Order Hex Keys Separately

Hand Assembly Tools For Frangible Collars

Extra Strong Hex Keys to be used for manual installation and removal of fasteners



Hex Key Part Number	Handle Part Number (Optional)	Screw Dia.	Hex Size	"A" Reference (inches)	"B" Reference (inches)
HK650-078-1	HKH105-078	-5, -6	5/64" (.078)	0.50	3.20
HK650-078-2	HKH105-078	-5, -6	5/64" (.078)	0.75	3.20
HK650-078-3	HKH105-078	-5, -6	5/64" (.078)	2.09	4.45
HK650-094-1	HKH105-094	-8	3/32" (.094)	0.50	3.50
HK650-094-2	HKH105-094	-8	3/32" (.094)	0.75	3.25
HK650-094-3	HKH105-094	-8	3/32" (.094)	2.09	4.45
HK650-125-4	Not Available	-10	1/8" (.125)	1.25	5.25
HK650-125-3	Not Available	-10	1/8" (.125)	2.40	4.10
HK650-156-3	Not Available	-12	5/32" (.156)	2.40	4.10
HK650-156-4	Not Available	-12	5/32" (.156)	1.25	5.25

Material: High Strength Alloy Steel

Caution: Do not use these hex keys with power installation tooling

Hand Assembly Tools For Frangible Collars

Roller Wrenches, up to 400 in-lbs




YSA Standard Collars

YSA 351, 352, 353, 361, 362, 363

Collar Dia.	Hex Size (mm)	Socket Part Number	Roller Wrench	Socket Drive	"A" (mm)	"C" (mm)	Socket Length	Hex Key (Metric)	Hex Key Handle, Type 1	Hex Key Handle, Type 2
-4	6	CTSM-6-1	RWB100-80	1/4"	49.8	7.1	22.2mm	HK660-M1.5-1	HKHM-1.5	HKH100
-4	6	CTSM-6-2	RWB100-80	1/4"	76.8	7.1	49.2mm	HK660-M1.5-2	HKHM-1.5	HKH100
-5	7	CTSM-7-1	RWB100-80	1/4"	49.8	7.1	22.2mm	HK660-M2-1	HKHM-2.0	HKH100
-5	7	CTSM-7-2	RWB100-80	1/4"	76.8	7.1	49.2mm	HK660-M2-2	HKHM-2.0	HKH100
-6	8	CTSM-8-1	RWB100-150-375	3/8"	39.0	11.2	25.4mm	HK660-M2.5-1	HKHM-2.5	HKH100
-6	8	CTSM-8-2	RWB100-150-375	3/8"	66.0	11.2	50.8mm	HK660-M2.5-2	HKHM-2.5	HKH100
-8	10	CTSM-10-1	RWB100-400	3/8"	45.3	15.9	25.4mm	HK660-M3-1	HKHM-3.0	HKH100
-8	10	CTSM-10-2	RWB100-400	3/8"	70.7	15.9	50.8mm	HK660-M3-2	HKHM-3.0	HKH100

Metric Hex Keys For Frangible Collars

Extra Strong Metric Keys to be used for manual installation and removal of fasteners




Part Number	Bolt Dia.	Hex Size	"A" Reference		"B" Reference	
			In	mm	In	mm
HK650-M1.5-1	-4	1.5mm	1.0"	25.4	5.7"	147.3
HK650-M1.5-2	-4	1.5mm	2.5"	63.5	4.3"	109.2
HK650-M1.5-3	-4	1.5mm	3.3"	83.8	3.5"	88.9
HK650-M2-1	-5	2.0mm	1.0"	25.4	5.7"	147.3
HK650-M2-2	-5	2.0mm	2.5"	63.5	4.3"	109.2
HK650-M2-3	-5	2.0mm	3.3"	83.8	3.5"	88.9
HK650-M2.5-1	-6	2.5mm	1.0"	25.4	5.8"	147.3
HK650-M2.5-2	-6	2.5mm	2.0"	50.8	4.8"	121.9
HK650-M2.5-3	-6	2.5mm	3.0"	76.2	3.8"	96.5
HK650-M3-1	-8	3.0mm	1.2"	30.5	5.6"	142.0
HK650-M3-2	-8	3.0mm	2.2"	55.8	4.6"	116.8
HK650-M3-3	-8	3.0mm	3.2"	81.3	3.6"	91.4

Material: High Strength Alloy Steel

Caution: Do not use these hex keys with power installation tooling

Handle for Forged Metric Hex Keys




This is an economical handle for holding forged Metric Size Hex Keys. This handle is comfortable to hold and the hex keys are retained by a standard set screw. This handle and key assembly are ideal for manually installed nuts or frangible collars on pins with a metric size hex recess.

The hex keys come in a standard length of 3.0" [76.2mm] and can be shortened for tighter fit applications.

Type 1 Handle

Handle Part Number	Hex Key Part Number	Description	Collar Dia.	Hex Key Length
HKHM-1.5	HK660-M1.5-1	Hex Key 1.5mm	-4	2.5" [63.5mm]
HKHM-1.5	HK660-M1.5-2	Hex Key 1.5mm	-4	3.3" [85.6mm]
HKHM-2.0	HK660-M2-1	Hex Key 2.0mm	-5	2.5" (63.5mm)
HKHM-2.0	HK660-M2-2	Hex Key 2.0mm	-5	3.3" [85.6mm]
HKHM-2.5	HK660-M2.5-1	Hex Key 2.5mm	-6	2.0" [50.8mm]
HKHM-2.5	HK660-M2.5-2	Hex Key 2.5mm	-6	3.0" [76.2mm]
HKHM-3.0	HK660-M3-1	Hex Key 3.0mm	-8	2.2" [55.9mm]
HKHM-3.0	HK660-M3-2	Hex Key 3.0mm	-8	3.2" [81.3mm]

Handle for Forged Aster™ Keys



This is an economical handle for holding Aster™ keys. This handle is comfortable to hold and the keys are retained by a standard set screw. This handle and key assembly are ideal for manually installed nuts or frangible collars on pins with the Aster™ recess.

The keys come in a standard length of 3.0" [76.2mm] and can be shortened for tighter fit applications.

Caution: **To avoid injury, do not use this wrench design with power installation tooling**


Ordering Numbers	Description	Aster™ Key Length
HKH100	Handle	3.0" (76.2mm)
AK650-2-B	Aster™ Key for -2 Dia. Pin	3.0" (76.2mm)
AK650-3-B	Aster™ Key for -3 Dia. Pin	3.0" (76.2mm)
AK650-3A-B	Aster™ Key for -3A Dia. Pin	3.0" (76.2mm)
AK650-4-B	Aster™ Key for -4 Dia. Pin	3.0" (76.2mm)

Note: Aster™ is a trademark of Blanc Aero Industries

Length of the Aster™ Key can be adjusted to fit application requirements

Aster™ Key Accessories For Nuts and Frangible Collars

Extra Strong Aster™ Keys to be used for manual installation and removal of fasteners



AKH105 handles are optional equipment and must be ordered separately

Aster™ Key is not formed on both ends


Hex Key Part Number	Handle Part Number (Optional)	Screw Dia.	"A" Reference (mm)	"B" Reference (mm)
AK650-2-16	AKH105-2	-2	16.0	85.0
AK650-3-16	AKH105-3	-3	16.0	85.0
AK650-3A-16	AKH105-3A	-3A	16.0	85.0
AK650-4-17	AKH105-4	-4	17.0	85.0

Material: High Strength Alloy Steel

Caution: Do not use this product with a power tool, serious injury can occur.

Aster™ Key Accessories For Nuts and Frangible Collars

Extra Strong Aster™ Keys to be used for manual installation and removal of fasteners



AKH105 handles are optional equipment and must be ordered separately

Aster™ Key is not formed on both ends

Hex Key Part Number	Handle Part Number (Optional)	Screw Dia.	"A" Reference (mm)	"B" Reference (mm)
AK650-2-16	AKH105-2	-2	16.0	85.0
AK650-3-16	AKH105-3	-3	16.0	85.0
AK650-3A-16	AKH105-3A	-3A	16.0	85.0
AK650-4-17	AKH105-4	-4	17.0	85.0

Material: High Strength Alloy Steel

Caution: Do not use this product with a power tool, serious injury can occur.

Frangible Collars Tools


Collar Removal Tools Pneumatic and Hand Tools

SECTION 6



Hand Removal Tool For Frangible Collars

Crow Foot Removal Wrenches




Features:

- Crows foot jaw securely grips frangible collars for their easy removal in restricted areas
- Tool is made of heat treated high grade steel
- Various lengths, user provided, extenders permit tool usage in deep channels

Part Number	Collar Usage	Edge Radius	"S" Square	H	D
RT100-56CF	-5, -6	.280	.25	0.28	1.010
RT100-8CF	-8	.350	.25	0.38	1.170
RT100-10CF	-10	.430	.375	0.47	1.450
RT100-12CF	-12	.430	.375	0.47	1.450
FT100-14CF	-14	.610	.375	0.57	1.800

Hand Removal Tool For Frangible Collars



FEATURES:

- SERRATED REMOVAL TOOL SECURLY GRIPS FRANGIBLE COLLARS FOR EASY REMOVAL
- TOOL IS AVAILABLE WITH AN OFFSET OR STRAIGHT HANDLE


Removal Tool Offset Handle

Part Number	Collar Diameter	R	T	L	W
RT100-56	-5, -6	.280	.28	5.6"	.42
RT100-8	-8	.350	.38	5.8"	.55
RT100-10	-10	.430	.47	6.9"	.67
RT100-12	-12	.430	.47	6.9"	.67
RT100-14	-14	.610	.57	9.9"	.95

Removal Tool Straight Handle

Part Number	Collar Diameter	R	T	L	W
RT100-56S	-5, -6	.280	.28	5.6"	.42
RT100-8S	-8	.350	.38	5.8"	.55
RT100-10S	-10	.430	.47	6.9"	.67
RT100-12S	-12	.430	.47	6.9"	.67
RT100-14S	-14	.610	.57	9.9"	.95


Hand Removal Tool For Frangible Collars



Roller Wrench Removal Tools for Frangible Collars

Collar Dia.	Removal Socket	Roller Wrench	Hex Key Size	Hex Key Bit 2.5" Long	Handle for Hex Key Bit
(-5) 5/32"	CRTS9000-5	RT9001-375	.062 (1/16")	TBD	SPKH-5S
(-5) 5/32"	CRTS9000-5	RT9001-375	.078 (5/64")	093-9323	SPKH-6S
(-6) 3/16"	CRTS9000-6	RT9001-375	.078 (5/64")	093-9323	SPKH-6S
(-8) 1/4"	CRTS9000-8	RT9001-375	.094 (3/32")	093-9325	SPKH-8S

Hand Removal Tool For Frangible Collars



Roller Wrench Removal Tools for Frangible Collars

Collar Dia.	Removal Socket	Roller Wrench	Hex Key Size	Hex Key Bit 2.5" Long	Handle for Hex Key Bit
(-8) 1/4"	CRTS9000-8	RT9000-375	.094 (3/32")	093-9325	SPKH-8S
(-10) 5/16"	CRTS9000-10	RT9000-375	.125 (1/8")	093-9008	SPKH-10S
(-12) 3/8"	CRTS9000-12	RT9000-375	.156 (5/32")	TBD	SPKH-12S

Hand Removal Tool For Frangible Collars

Procedure for removing frangible collars:

1. Select the correct size removal socket for the fastener that will be removed.
2. Attach the appropriate size removal socket to the ratchet wrench or roller wrench.
3. Place the removal socket over the frangible collar that you want to remove and apply a moderate amount of down pressure. Turn the socket in a counter-clockwise direction to loosen the collar.
4. If the “screw” or “pin” is not tight and turns with the collar when you attempt to loosen it, you will need the appropriate size hex key to hold the “pin” from turning while you rotate the nut. The hex key will fit through the ratchet wrench and socket and fit into the hex recess of the “pin”.
5. Removing the socket from the collar can be difficult. Before the collar is completely removed from the “pin” it is recommended to wiggle the socket which will detach it from the collar. You should be able to remove the collar by hand at this time.



ARCONIC

Arconic Fastening Systems

Assembly Tool Systems Division

801 S. Placentia Avenue
Fullerton, CA USA 92831
714-278-8908 Telephone
714-871-4821 FAX